



RF Wireless Tablet

The TouchIT Tablet™ uses RF wireless technology so teachers and students can enjoy the freedom of controlling their individual computers or digital content displayed on the Interactive Whiteboard from anywhere in the classroom via 2.4G wireless technology.



Interactive 2.4G RF Tablet

TOTAL CONTROL FROM ANYWHERE IN THE ROOM...

Product Highlights

- RF 2.4G Tablet with a 10m range
- Truly plug and play. No driver installation required for basic mouse-like functionality
- Miniature USB RF Receiver, no large intrusive dongle required
- Control and annotate your PC or MAC from anywhere in the room.
- Increase audience participation without the need for anyone to leave their seats
- Powered by standard batteries (1 x AAA & 2 x AA)

Product Specification

| | |
|----------------------|--|
| Technology | Electromagnetic |
| Active Area | 5 x 3.25" |
| Resolution | 2000 LPI |
| Position Accuracy | +/- 0.01" |
| Pressure Sensitivity | 1024 levels |
| Report Rate | 200 RPS |
| Reading Height | 10mm |
| Power Supply | Battery AAA X 2 or Mini USB 5V |
| Input Current | < 45mA |
| Standby and Wake up | Auto |
| Power Consumption | 35 mA (max / 3V 10-35 mA (operation) 66 uA (Standby) |
| Time to Standby | 5 Mins |
| Weight | 342g |
| Dimensions (L*W*H) | 190*194*18.5mm |
| Transmission | RF |
| Receiver Interface | USB 1.1 |
| Transmission Range | 10m |
| Stylus | |
| Power Source | Battery AAA x 1 |
| Battery Life | 4000 hours (average) |
| Standby and Wake Up | Auto |
| Power Consumption | 180 uA (operation) 2.5 uA (standby) |
| Time to Standby | 10 mins |
| Weight | 23g |
| Dimensions (L*W*H) | 137 x 12 x 16.4mm |

Package Contents

- 1 x TouchIT Tablet
- 1 x Software CD
- 2 x AA Battery
- 1 x AAA Battery
- 1 x USB RF Receiver
- 1 x Quick Start Guide
- 1 x TouchIT Tablet Stylus
- 1 x USB Cable
- 1 x Spare Nibs

Bundled Software

- PenNotice
- PenSigner
- PenMail
- Adobe PhotoShop CS3 (30 Days Trial) (Win XP / Vista)
- Corel Painter X (30 Days Trial) (Win 2K / XP / Vista)
- Annotate for Word (Not Vista)
- Pen Commander (Not Vista)



RECOMMENDED SPECIFICATION

- Microsoft® Windows® XP with Service Pack 2 or Windows® Vista
- MAC OS X 10.4 or above
- DVD-ROM Drive
- Available USB Port

For more information contact us by email
sales@touchittechnologies.com
www.touchittechnologies.com